



## Nura4K 5G Camera

<b>Processor</b>	Sigmastar SAV536G (CameraSoC) <ul style="list-style-type: none"><li>- Dual Cortex A7@1.2Ghz, 1 TOPs CNN</li><li>- DDR3L 2Gb x2</li><li>- NAND Flash 1Gb</li></ul> <hr/> Qualcomm, SDX62 (Cellular) <ul style="list-style-type: none"><li>- Quectel RM520N-GL Modem</li></ul> <hr/> Broadcom BCM43435 (Wi-Fi 5 BT Combo) <ul style="list-style-type: none"><li>- Ampak AP6256 SiP Module</li></ul>	<b>Connectivity</b>	Supported 5G and LTE Networks * [NA] n2/5/12/13/25/41/48/66/71/77/78 B2/4/5/12/13/25/66/71 [EU] n1/3/7/8/20/28/38/40/41/48/78/79 B1/3/7/8/20/28  Wi-Fi 802.11 a/b/g/n/ac Dual Band 1x1 Bluetooth 5.2
<b>OS</b>	Linux Kernel v4.9.84	<b>Audio</b>	3-Watt Speaker High Sensitivity D-Microphone <ul style="list-style-type: none"><li>- Two-way talk</li><li>- Echo Cancelling, Noise Reduction</li></ul>
<b>Sensor</b>	Sony IMX415 <ul style="list-style-type: none"><li>- 1/2.8", 3840x2160@90fps, 1.45 µm</li><li>- 4K UHD, BI, DOL HDR, 0.79lx (SNR1)</li><li>- MIPI CSI-2</li></ul> <hr/> High Resolution Full Glass Lens <ul style="list-style-type: none"><li>- F1.8, M12 Mount</li><li>- Construction: 7G</li><li>- FOV 110(H) x 58(v) x 132(D)</li></ul>	<b>Others</b>	Ambient Light Sensor 2x IR LED for Night Vision (8-Meter) 1x RGB LED for Status Indication Reset Button, Nano SIM Card Slot
		<b>Power</b>	36W USB-C PD Adapter (15V/2.4A)
		<b>Operating</b>	IP65, -10°C ~ 50°C (Indoor Type) 72.5 mm x 73 mm x 123.5 mm Always-On Sensing

\* Supported and certified frequency bands vary by product SKU and by country. Contact us for details.

